

# 1, 2 & 3 Channel Receivers



## Applications

- Gate & Garage Door Access Control
- Panic Activations
- Arming/Disarming Alarm systems
- Switching On/Off lights
- Switching On/Off Generators

## Features

- Code-Hopping Encryption
- Latch or Momentary
- Selectable Momentary times:
  - 1 Sec; 3Sec; 1min; 3min
- Buzzer tone
- Crystal Controlled +/- 100KHz
- Frequencies: 403MHz/433MHz
- 12 - 24V AC/DC input

## Certifications

- ETSI EN300 220-V2.4.1
- IEC 60950-1:2005 + A1:2009
- ETSI EN301-489-3 V1.4.1
- ETSI EN301-489-1 V1.9.2
- ICASA TA-2017/1846 - RX1-150
- ICASA TA-2017/1845 - RX2-150
- ICASA TA-2017/1755 - RX3-150

Description	Order Code
1 Channel Receiver	RX1-150
2 Channel Receiver	RX2-150
3 Channel Receiver	RX3-150
1 Ch BUSLINE Receiver	BUSRX
BUSLINE Receiver KIT	BUSRX_KIT



## Specifications

- Encryption: Code-Hopping
- Range: 150m (Open air)
- Frequency: 403MHz / 433 MHz
- Memory Capacity:-
  - RX1-150 80 Remotes
  - RX2-150 40 Remotes
  - RX3-150 32 Remotes
- Voltage Range: 9.8V to 26V AC/DC
- Current draw: 15mA
- Dimensions (lxbxh):
  - 68 x 45 x 23mm - RX1-150
  - 80 x 60 x 23mm - RX2-150 / RX3-150
- Weight RX1-150: 50grams
- Weight RX2-150: 75grams
- Weight RX3-150: 85grams
- Operating Temp: -5°C to 60°C
- Warranty: 24 Months